

1N-33
169426

P-9

Microwave Characterization of Slotline on High Resistivity Silicon for Antenna Feed Network

Rainee N. Simons
Sverdrup Technology, Inc.
Lewis Research Center Group
Brook Park, Ohio

Susan R. Taub and Richard Q. Lee
National Aeronautics and Space Administration
Lewis Research Center
Cleveland, Ohio

and

Paul G. Young
University of Toledo
Toledo, Ohio

(NASA-TM-106058) MICROWAVE
CHARACTERIZATION OF SLOTLINE ON
HIGH RESISTIVITY SILICON FOR
ANTENNA FEED NETWORK (NASA) 9 p

N93-27265

Unclass

G3/33 0169426

Prepared for the
1992 IEEE AP-S International Symposium and URSI Radio Science Meeting
sponsored by the IEEE and USNC Commissions A, B, D, and F
Ann Arbor, Michigan, June 27-July 2, 1993



MICROWAVE CHARACTERIZATION OF SLOTLINE ON HIGH RESISTIVITY

SILICON FOR ANTENNA FEED NETWORK

Rainee N. Simons, Susan R. Taub,
Richard Q. Lee, and Paul G. Young
National Aeronautics and Space Administration
Lewis Research Center
Cleveland, Ohio 44135

ABSTRACT

This paper presents, the effective dielectric constant (ϵ_{eff}) and attenuation constant (α) of a unshielded slotline on a high resistivity (5000 to 10,000 $\Omega\text{-cm}$) silicon wafer. The ϵ_{eff} (DC to 40 GHz) and α (DC to 26.5 GHz) are determined from the measured resonant frequencies and the corresponding insertion loss of a slotline ring resonator. The measurements are carried out at room temperature and without the application of a DC bias. The attenuation for slotline on silicon are compared with microstrip line and coplanar waveguide on other semiconductor substrate materials. Finally, applications of the slotline to antenna feed network are addressed.

I. INTRODUCTION

There are several reasons why silicon is now a viable microwave material. One reason is that silicon MOSFET's with cutoff frequencies as high as 89 GHz have been reported (ref.1). Another, is that silicon MMIC amplifiers, mixers and IMPATT diodes are now commercially available (refs. 2 thru 4). The final reason is that transmission lines, such as, microstrip line (refs. 5 thru 9) and Coplanar Waveguide (CPW) (ref. 10) with low loss have been demonstrated on high resistivity silicon. Silicon has several advantages over GaAs and InP technologies, such as: better thermal conductivity, higher reliability, higher circuit complexity, availability of wafers of very large diameters, better mechanical properties, and lower cost (ref. 9). Furthermore, integration of MMIC's with digital control circuits and radiating elements on a single silicon wafer is possible. This can enhance the reliability, efficiency and lower the cost of phased array antenna systems. However, silicon substrates do have slightly higher dielectric loss than traditional microwave substrates. DC bias and high operating temperatures can increase this loss. Additional loss can be introduced, if during processing, the wafers are exposed to temperatures high enough to significantly lower their resistivity (ref. 9).

Conventional silicon wafers have low resistivity and consequently an unacceptably high value of dielectric attenuation. Therefore, microwave circuits for phased array antenna systems fabricated on these wafers have low efficiency. By choosing a silicon substrate with sufficiently high resistivity it is possible to make the dielectric attenuation of the interconnecting microwave transmission lines approach those of GaAs or InP (refs. 6 and 7).

In order to fabricate microwave circuits on silicon, the transmission lines on this material must be characterized. Recently, the attenuation of microstrip transmission lines on high resistivity, bare and passivated silicon as a function of frequency, temperature and DC bias have been measured (ref. 9). Also, attenuation and ϵ_{eff} of CPW lines as a function of resistivity, frequency and geometry on silicon substrates has been examined experimentally and theoretically (ref. 10). This paper presents the effective dielectric constant (ϵ_{eff}) and attenuation constant (α) of an unshielded slotline on a high resistivity (5000 to 10,000 $\Omega\text{-cm}$) silicon wafer over the frequency ranges DC to 40 GHz and DC to 26.5 GHz respectively. The measurements are carried out at room temperature and without the application of a DC bias.

II. THEORY

An experimental slotline ring resonator is shown in figure 1. The advantage of a ring resonator over a series gap coupled linear resonator is that the ring resonator is free of end effects. The loaded Q-factor, Q_L , of the resonator is determined from the following equation relating the measured resonance frequency, f_0 , and the frequency range, Δf , between the 3-dB points on either side of the resonance:

$$Q_L = f_0 / \Delta f. \quad (1)$$

The unloaded Q-factor, Q_u , of the resonator is determined from the following equation relating the measured peak insertion loss, L , at resonance and Q_L :

$$L \text{ (dB)} = 20 \text{ Log } \{1 - [Q_L/Q_u]\}. \quad (2)$$

The ϵ_{eff} is determined from the following equation:

$$\epsilon_{\text{eff}} = (30 n/f_0 l)^2 \quad (3)$$

Where n is an integer and denotes the order of resonance. Therefore for n resonances of a particular resonator, n values of ϵ_{eff} can be obtained. l is the mean circumference of the ring in cm. f_0 is in GHz.

The phase velocity, v_{ph} , of the electromagnetic wave on the slotline is equal to

$$v_{\text{ph}} = 3 \times 10^8 / \sqrt{\epsilon_{\text{eff}}} \text{ (mt/sec)}. \quad (4)$$

Finally, the attenuation constant α of the slotline is determined from the relation:

$$\alpha = \pi f_0 / Q_u v_{\text{ph}} \text{ (Np/mt)}. \quad (5)$$

III. RESONATOR FABRICATION AND EXPERIMENTAL RESULTS

The slotline ring resonator is fabricated on a silicon wafer which is coated sequentially with 700 Å of silicon dioxide, 200 Å of chromium and 2.5 μm of gold. The thickness, T , of the gold metalization is greater than three times the skin depth at 8.5 GHz and above. The measured resistivity of the silicon dioxide layer is 10^{14} Ω-cm. The ϵ_{eff} and α are determined by substituting the measured resonant frequencies and the corresponding insertion loss in equations 1 thru 5. Figure 2 presents the ϵ_{eff} as a function of the frequency. In this figure the slot width W , wafer thickness D , and relative dielectric constant ϵ_r , are equal to 0.1 mm, 0.381 mm and 11.7, respectively. Also shown in Fig.2 is the computed ϵ_{eff} which is obtained as described in ref.11. The measured and computed ϵ_{eff} are in good agreement.

The intrinsic peak insertion loss L of the resonator is corrected for the insertion loss due to the microstrip feed lines and the coaxial connectors of the fixture. This is done by subtracting the feed and connector loss from the overall measured insertion loss. These excess losses are determined from a separate set of measurements using a thru line of length equal to the sum of the feed line lengths in the test fixture. Figure 3 presents the measured attenuation α as a function of the frequency. The W , D and ϵ_r of the slotline are the same as those in Fig. 2. The attenuation of slotline is compared in Table 1 with the measured results from the open literature for microstrip line and coplanar waveguide on various other semiconductor substrate materials. It is worth mentioning here that the attenuation values quoted in Table 1 depend on the substrate thickness, metalization thickness and also the strip conductor width and/or slot width which are not the same in all cases.

IV. CONCLUSIONS AND DISCUSSIONS

The ϵ_{eff} and α for a slotline on a high resistivity silicon substrate have been experimentally obtained. The attenuation constant for slotline has been compared with that of microstrip line and coplanar waveguide on other semiconductor substrate materials. The value of attenuation for slotline was found to be comparable to other transmission lines. This, however, can only be a rough comparison because attenuation depends upon the substrate thickness, metalization thickness and strip conductor width and/or slot width which are not the same in all the cases. However our experiments demonstrate the viability of high resistivity silicon for low loss antenna feed network. Application of this information to the feed network will be presented at the symposium.

REFERENCES

1. Yan, R.H., et al.: 89-GHz f_T Room-Temperature Silicon MOSFET's, IEEE Electron Device Letters, Vol. 13, No. 5, pp. 256-258, May 1992.
2. Hanes, M.H., et al.: MICROXTM -An All-Silicon Technology for Monolithic Microwave Integrated Circuits, IEEE Electron Device Letters, Vol. 14, No.5, pp. 219-221, May 1993.
3. Hewlett Packard Communications Components, GaAs and Silicon, Designers Catalogue, Section 8, 1993.
4. Hughes millimeter Wave Products Catalogue.
5. Hyltin, T.M.: Microstrip Transmission on Semiconductor Dielectrics, IEEE Trans. Microwave Theory Tech., Vol.MTT-13, No.6, pp.777-781, Nov. 1965.
6. Young, L. and H. Sobel (Editors), Advances in Microwaves, Vol.8, Academic Press, New York, New York, 1974, pp. 19-25.
7. Rosen, A., et al.: Silicon as a Millimeter-Wave Monolithically Integrated Substrate - A New Look, RCA Rev., Vol. 42, pp. 633-660, 1981.
8. Caviglia, A.L. et al.: Microwave Performance of SOI n-MOSFET's and Coplanar Waveguides, IEEE Electron Device Letters, Vol.12, No.1, pp.26-27, Jan. 1991.
9. Levesque, K., et al.: Microwave Characterization of High Resistivity Silicon, Microwave Hybrid Circuits Conf., Oct. 1992.
10. Taub, S.R. and P.G. Young: Attenuation and ϵ_{eff} of Coplanar Waveguide Transmission Lines on Silicon Substrates, Eleventh Annual Benjamin Franklin Symposium on Antenna and Microwave Technology in the 1990s Digest, pp.8-11, May 1993.
11. Simons, R.N.: Suspended Slot Line Using Double Layer Dielectric, IEEE Trans. Microwave Theory Tech., Vol. MTT-29, No. 10, pp.1102-1107, Oct.1981.
12. Higgins J.A.: Microwave GaAs FET Monolithic Circuits, 1979 IEEE Inter. Solid-State Circuits Conf. Digest of Tech. Papers, pp. 120-121.
13. Haydl, W.H. et al.: Millimeterwave Coplanar Transmission Lines on Gallium Arsenide, Indium Phosphide and Quartz with Finite Metalization Thickness, 1991 IEEE MTT-S Inter. Microwave Symp. Digest, pp. 691-694, 1991.

14. Haydl, W.H.,: Experimentally Observed Frequency Variation of the Attenuation of Millimeter-Wave Coplanar Transmission Lines with Thin Metalization, IEEE Microwave & Guided Wave Letters, Vol.2, No.8, pp.322-324, Aug. 1992.

TABLE 1
Comparison of Attenuation Constant of Microwave Transmission
Lines on Semiconductor Substrates

TRANSMISSION LINE	SUBSTRATE MATERIAL	DIMENSIONS (Inch)	ATTENUATION @ 10 GHz (dB/cm)	REFERENCE
Microstrip ($Z_0 = 50 \Omega$)	SI GaAs	D = 0.025 W = 0.025 T = 3 μm^*	0.105	12
Coplanar Waveguide (CPW) ($Z_0 \approx 50 \Omega$)	SI GaAs	D = 0.025 S = 0.025 W = 0.0125 T = 3 μm^*	0.16	12
Coplanar Waveguide (CPW) ¹ ($Z_0 \approx 35 \Omega$)	SI InP	D = 0.5 mm S = 88 μm W = 16 μm T = 0.25 μm^*	4.5	14
Coplanar Waveguide (CPW) ($Z_0 = 50 \Omega$)	SI GaAs	D = 0.5 mm S = 75 μm W = 56 μm T = 3 μm^*	0.45	13
Microstrip ($Z_0 = 50 \Omega$)	High Res. silicon (1.5 k $\Omega\text{-cm}$)	D = 0.01 W = 0.006 [§]	0.5	5
Microstrip ($Z_0 \approx 50 \Omega$)	High Res. Silicon (8 k $\Omega\text{-cm}$)	D = 0.021 W = 0.016 T \approx 3 μm	0.16	9
Coplanar Waveguide (CPW) ² ($Z_0 \approx 50 \Omega$)	High Res. Silicon (2.5 - 3.3 k $\Omega\text{-cm}$)	D = 0.008 S = 0.004 W = 0.002 T = 2.5 μm^*	0.62	10
Coplanar Waveguide (CPW) ² ($Z_0 \approx 60 \Omega$)	High Res. Silicon (4 k $\Omega\text{-cm}$)	D = 400 μm S = 30 μm W = 35 μm T = 1 $\mu\text{m}^§$	3	8
Slotline ² ($Z_0 = 60 \Omega$)	High Res. Silicon (5 - 10 k $\Omega\text{-cm}$)	D = 0.015 W = 0.004 T = 2.5 μm^*	0.25	This work

D is substrate thickness and T is metalization thickness

Microstrip: W is strip width

Coplanar Waveguide: S is center strip width and W is slot width

¹Metal thickness less than one skin depth

²A SiO₂ interfacial layer is present

*Gold conductors, [§]Aluminium conductors




Figure 1.—Slotline ring resonator electromagnetically coupled to microstrip feed lines.




Figure 2.—Effective dielectric constant.




Figure 3.—Attenuation constant.

REPORT DOCUMENTATION PAGE			Form Approved OMB No. 0704-0188	
Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.				
1. AGENCY USE ONLY (Leave blank)		2. REPORT DATE March 1993		3. REPORT TYPE AND DATES COVERED Technical Memorandum
4. TITLE AND SUBTITLE Microwave Characterization of Slotline on High Resistivity Silicon for Antenna Feed Network			5. FUNDING NUMBERS WU-506-44-2C	
6. AUTHOR(S) Rainee N. Simons, Susan R. Taub, Richard Q. Lee, and Paul G. Young				
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) National Aeronautics and Space Administration Lewis Research Center Cleveland, Ohio 44135-3191			8. PERFORMING ORGANIZATION REPORT NUMBER E-7659	
9. SPONSORING/MONITORING AGENCY NAMES(S) AND ADDRESS(ES) National Aeronautics and Space Administration Washington, D.C. 20546-0001			10. SPONSORING/MONITORING AGENCY REPORT NUMBER NASA TM-106058	
11. SUPPLEMENTARY NOTES Prepared for the 1993 IEEE AP-S International Symposium and URSI Radio Science Meeting sponsored by the IEEE and USNC Commissions A,B,D, and F, Ann Arbor, Michigan, June 27-July 2, 1993. Rainee N. Simons, Sverdrup Technology, Inc., Lewis Research Center Group, 2001 Aerospace Parkway, Brook Park, Ohio 44142; Susan R. Taub and Richard Q. Lee, Lewis Research Center; and Paul G. Young, University of Toledo, Toledo, Ohio 43606. Responsible person, Rainee N. Simons, (216) 433-3462.				
12a. DISTRIBUTION/AVAILABILITY STATEMENT Unclassified - Unlimited Subject Category 33			12b. DISTRIBUTION CODE	
13. ABSTRACT (Maximum 200 words) Conventional silicon wafers have low resistivity and consequently unacceptably high value of dielectric attenuation constant. Microwave circuits for phased array antenna systems fabricated on these wafers therefore have low efficiency. By choosing a silicon substrate with sufficiently high resistivity it is possible to make the dielectric attenuation constant of the interconnecting microwave transmission lines approach those of GaAs or InP. In order for this to be possible, the transmission lines must be characterized. In this presentation, the effective dielectric constant (ϵ_{eff}) and attenuation constant (α) of a slotline on high resistivity (5000 to 10 000 Ω -cm) silicon wafer will be discussed. The ϵ_{eff} and α are determined from the measured resonant frequencies and the corresponding insertion loss of a slotline ring resonator. The results for slotline will be compared with microstrip line and coplanar waveguide.				
14. SUBJECT TERMS High resistivity silicon; Slotline; Effective dielectric constant, Attenuation			15. NUMBER OF PAGES 8	
			16. PRICE CODE A02	
17. SECURITY CLASSIFICATION OF REPORT Unclassified	18. SECURITY CLASSIFICATION OF THIS PAGE Unclassified	19. SECURITY CLASSIFICATION OF ABSTRACT Unclassified	20. LIMITATION OF ABSTRACT	

National Aeronautics and
Space Administration

Lewis Research Center
Cleveland, Ohio 44135

FOURTH CLASS MAIL

ADDRESS CORRECTION REQUESTED



Official Business
Penalty for Private Use \$300

NASA
